



sabena B707	Module: ENGINE 3	A/C Reg :	Check :	
	Oper. : RT-MP LC			
	Type : SERVICING	Issuer : A43710	Cert.St.: 24828	P1H1000504
Spec. : MECHANIC	Release Date: 17.10.2001		Page 1 of 3	

ENG #3 CSD OIL FILTER REPL

Execution / Start Date:	
End Date:	

MAINT **RII/INSP**

Pos	Mat. Type	P/N	IDN	Description	Qty	Unit
1	CONSUM	7578137-101	347239	FILTER	1.00	EA
1	CONSUM	7583142	346746	FILTER	1.00	EA
1	CONSUM	M 83248-1-014	421691	O RING	1.00	EA
1	CONSUM	M 83248-1-018	287842	O RING	1.00	EA
1	CONSUM	M 83248-1-128	287810	O RING	1.00	EA
1	CONSUM	MS 28782-19	865540	O RING	1.00	EA
1	CONSUM	MS 9388-214	548335	O RING	1.00	EA
1	CONSUM	MS 9388-228	291425	O RING	1.00	EA
1	FL & CH	28 075 3442		ACRYLOID HF 825	0.00	
1	FL & CH	28 033 1002		VASELINE	0.00	
1	TOOL	L-452A	150510	TORQUEMETER	1.00	EA
1	TOOL	L-465A	150508	TORQUEMETER	0.00	

sabena B707	Module: ENGINE 3	A/C Reg :	Check :	
	Oper. : RT-MP LC			
	Type : SERVICING	Issuer : A43710	Cert.St.: 24828	P1H1000504
	Spec. : MECHANIC	Release Date: 17.10.2001		Page 2 of 3

ENG #3 CSD OIL FILTER REPL

					MAINT	RII/INSP
Nr.	Hardtime	Task	Spec.	Related Documents		
1.		S	MEC	MMS-328 241003 00103 rev 15/05/01		
Check: C						
Zones: 453						
Access:						

NOTE: FILTER REPLACEMENT MUST BE PERFORMED TOGETHER WITH CSD OIL CHANGE REF. MS: 241002 00101

CSD OIL FILTERS REPLACEMENT.

CSD LINE FILTER REPLACEMENT:

1. Remove LINE OIL FILTER.
 - Remove locking wire.
 - Unscrew filter case & discard case O-ring.
 - Remove filter element & discard filter O-ring.
2. Install LINE OIL FILTER.
 - Replace filter O-ring inside mounth of filter element.
 - Replace filter element.
 - Coat filter thread with small amount of VASELINE.
 - Using new case O-ring, install filter case & tighten to 120-360 pound-inches & lockwire.

